



SALE PRE OWNED

**fjord 36 open**

**210 000 € All Tax Included**

## Description

Fjord 36 open 2012 single-owner very equipped joystick with autopilot t-top special paint inverter 1600W

Navigation equipment:

Rudder angle indicator, Radar Antenna, Chain counter, Display, DSC vhf, Joystick, Plotter with GPS antenna, Co-pilot seat.

Staging and technical:

Fume/Gas Detector, Engine Alarm, Bilge Alarm, Electric Engine Compartment Opening, Water pressure pump, Teak Side Decks, Special Colour, Deck Shower, Electric Flaps, Hard top, Flaps Indicators, Washbasin in the cockpit, Courtesy Lights, Underwater lights, Gangway, Platform, Automatic Bilge Pump, Manual Bilge Pump, Entry door, Teak Cockpit, Shorepower connector, Electric Windlass, swimming ladder, cockpit table, T-Top.

Domestic Facilities onboard:

Warm Water System, Waste Water Plant, Interior wooden floor, 12V Outlets, 220V Outlets, Black Water Tank, Electric Toilet.

Kitchen and appliances:

Galley, Burner, Deck Refrigerator.

Upholstery:

Hull Cover, Bow Cushions, Cockpit Cushions, T-Top Cover, Window Cover,

## Specifications

YEAR

2011

WIDTH

4.00

FUEL TANK CAPACITY

600

CABINS

1

ENGINE MANUFACTURER

Volvo Penta D 4

HORSE POWER

2 X 300 CV

LENGTH

10.80

DRAFT

0.90

GUESTS CRUISING

12

BATHROOMS

1

ENGINE HOURS

720

**General**

---

TYPE	BRAND	MODEL	GUESTS CRUISING
Motorboat	fjord	36 open	12
CURRENT LOCATION			
Veneto			

**Dimensions / Performance**

---

FUEL CAPACITY (L)	CRUISING SPEED (ND)	TOP SPEED (ND)
600	25	42

**Building / facilities**

---

AMOUNT OF CABINS	BERTHS	BATHROOM(S)
1	2	1

**Engine room**

---

ENGINE	NUMBER OF ENGINES HORSE POWER (CV)	ENGINE HOURS
Volvo Penta D 4	2 x 300	720

**Electricity / air conditioning**

---

ENGINE BATTERY	BATTERY CHARGER
----------------	-----------------

### Navigation equipment

---

GPS	RADAR	AUTO PILOT	VHF
NAVIGATION COMPASS	SONAR	SPEEDOMETER	ANCHOR

### Galley / Laundry / Entertainment

---

FREEZER

### Deck equipment

---

DECK SHOWER

### Safety equipment / miscellaneous

---

BILGE PUMP







